

建臺有限公司

地址：台南市崇善路205巷3號 · 電話：06-2684508 · Email: contact@chientail.com.tw

R型絕緣端子/圓型絕緣端子/O型絕緣端子規格

規格名稱	線徑(mm ²)	螺絲孔(mm)	電線直徑(mm)	AWG
RF 1.25-3	1.25	3	1.7	AWG 22~16
RF 1.25-3S	1.25	3	1.7	AWG 22~16
RF 1.25-4	1.25	4	1.7	AWG 22~16
RF 1.25-5	1.25	5	1.7	AWG 22~16
RF 1.25-6	1.25	6	1.7	AWG 22~16
RF 1.25-8	1.25	8	1.7	AWG 22~16
RF 1.25-10	1.25	10	1.7	AWG 22~16
RF 1.25-12	1.25	12	1.7	AWG 22~16
RF 2-3	2	3	2.3	AWG 16~14
RF 2-3S	2	3	2.3	AWG 16~14
RF 2-4	2	4	2.3	AWG 16~14
RF 2-5	2	5	2.3	AWG 16~14
RF 2-6	2	6	2.3	AWG 16~14
RF 2-8	2	8	2.3	AWG 16~14
RF 2-10	2	10	2.3	AWG 16~14
RF 2-12	2	12	2.3	AWG 16~14
RF 3.5-4	3.5	4	3	AWG 14~12
RF 3.5-5	3.5	5	3	AWG 14~12
RF 3.5-6	3.5	6	3	AWG 14~12
RF 3.5-8	3.5	8	3	AWG 14~12
RF 3.5-10	3.5	10	3	AWG 14~12
RF 3.5-12	3.5	12	3	AWG 14~12
RF 5.5-4	5.5	4	3.4	AWG 12~10
RF 5.5-5	5.5	5	3.4	AWG 12~10
RF 5.5-6	5.5	6	3.4	AWG 12~10
RF 5.5-8	5.5	8	3.4	AWG 12~10
RF 5.5-10	5.5	10	3.4	AWG 12~10
RF 5.5-12	5.5	12	3.4	AWG 12~10
RF 8-4	8	4	4.5	AWG 8
RF 8-4S	8	4	4.5	AWG 8
RF 8-5	8	5	4.5	AWG 8
RF 8-5S	8	5	4.5	AWG 8
RF 8-6	8	6	4.5	AWG 8
RF 8-8	8	8	4.5	AWG 8
RF 8-10	8	10	4.5	AWG 8
RF 8-12	8	12	4.5	AWG 8

規格名稱	線徑(mm ²)	螺絲孔(mm)	電線直徑(mm)	AWG
RF 14-4	14	4	5.8	AWG 6
RF 14-5	14	5	5.8	AWG 6
RF 14-6	14	6	5.8	AWG 6
RF 14-8	14	8	5.8	AWG 6
RF 14-10	14	10	5.8	AWG 6
RF 14-11	14	11	5.8	AWG 6
RF 14-12	14	12	5.8	AWG 6
RF 22-5	22	5	7.7	AWG 4
RF 22-5S	22	5	7.7	AWG 4
RF 22-6	22	6	7.7	AWG 4
RF 22-6S	22	6	7.7	AWG 4
RF 22-8	22	8	7.7	AWG 4
RF 22-8S	22	8	7.7	AWG 4
RF 22-10	22	10	7.7	AWG 4
RF 22-10S	22	10	7.7	AWG 4
RF 22-11	22	11	7.7	AWG 4
RF 22-12	22	12	7.7	AWG 4
RF 38-6	38	6	9.4	AWG 2
RF 38-6S	38	6	9.4	AWG 2
RF 38-8	38	8	9.4	AWG 2
RF 38-8S	38	8	9.4	AWG 2
RF 38-10	38	10	9.4	AWG 2
RF 38-10S	38	10	9.4	AWG 2
RF 38-11	38	11	9.4	AWG 2
RF 38-12	38	12	9.4	AWG 2